

IMPORTANT SAFEGUARDS READ AND FOLLOW ALL SAFETY INSTRUCTIONS.

When using electrical equipment, basic safety precautions should always be followed including the following:

- **DISCONNECT AC POWER SUPPLY BEFORE SERVICING.**
- Installation and servicing of this equipment should be performed by qualified service personnel only.
- Ensure that the electrical wiring conforms to the National Electrical Code NEC® and local regulations if applicable.
- Do not mount near gas or electrical heaters.
- Equipment should be mounted in locations and at heights where it will not be readily subjected to tampering by unauthorized personnel.
- The use of accessory equipment not recommended by the manufacturer may cause an unsafe condition.
- Any modification or use of non-original components will void the warranty and product liability.
- Do not use this equipment for other than intended use.

SAVE THESE INSTRUCTIONS!

Technical Support ■ (623) 580-8943 ■ technicalsupport@barronltg.com

1. Locate support clips on back of panel quantity 4 or 6 depending on light fixture Fig. 1.
2. Mark corresponding mounting locations on ceiling surfaces 4 or 6 depending on model.
3. Affix each cable assembly to ceiling with appropriate fasteners (not supplied).
4. Position panel and attach spring clips on cable assemblies to holes on corresponding support clips. Use one cable assembly for each support clip.
5. Depress plunger pin on adjustable cable locks to adjust cables for even support and height for wiring.
6. Make wiring connections per fixture instructions and applicable codes.
7. Depress plunger pins and adjust height and level of each cable assembly as required for desired height, level and even support.
8. Add any additional support if required by code.
9. Verify security of installation.
10. Installation complete.

